



Shenzhen Bvsion Technology Co., Ltd.

Tel: 0086 755 23059953 Mobile: 0086-13924666965 / 00852-9373 7704 WhatsApp: +852 93737704

E-Mail: bvs.gina@lcdbvs.com Website: <http://www.lcdbvs.com> / <http://www.bvsipc.com>

Office Address: 5F, Building 9, Huafeng Science Park, Fengtang Avenue, Tangwei Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China, 518102.

Specification document

Model NO.	BVS-QR101	Standard	10.1", RK3288, 2+32GB, Android.
Brand name	BVS/OEM		
Product Type	Android Tablet PC		
Date	2026/7/18		



		Standard	optional
System	CPU	Rockchip RK3288	RK3399/RK3566/RK3568/RK3576/RK3588
	Frequency	UP to 1.8GHz	/
	GPU	Mail-T764	/
	NPU	/	/
	RAM	2GB	4GB/8GB
	EMMC	32GB	64GB/128GB
	Operating system	Android7.1/9.1	/
Display	Screen	10.1-inch touch screen display	10.1-inch non-touch display
	Resolution	1280*800	/
	Viewing angle	89/89/89/89 (Typ.)(CR≥10)	/
	Contrast ratio	800: 1	/
	Brightness	250 cd/m² (Typ.)	/
	Screen scale	16:09	/
Network	Wi-Fi	2.4G-Wi-Fi, supporting Wi-Fi 802.11b/g/n protocols	5G-Wi-Fi
	Ethernet	Gigabit network port	/
	BT	Bluetooth 3.0/3.0+HS/4.0	/
	4G LTE	NO	Customizable
Interfaces	USB	2	/
	COM	2	TTL/RS232/RS485
	HD	1	/
	TF card slot	1	/
	LAN	1	/
	SIM-4G	/	1
	DC-IN	1	/
Multi-Media	Video	MPEG-1,MPEG-2,MPEG-4,H.263,H.264,VC1,RV etc.,support up to 1080p	/
	Audio	MP3/WMA/AAC etc.	/
	Picture	jpeg, jpg	/
Accessories	Adapter	12V/5A	/
Temperature	Working temperature	-10~ 60°C	/
	Storage temperature	-20 ~ 70°C	/
Mounting	VESA Mount	(VESA Wall Mount)	(Swing Arm Mount/Ceiling Mount)
	Panel Mount	(Front Snap-in Panel Mount)	(Rear Flush Panel Mount)
	Stand Mount	Desktop Stand Mount	/
Packaging	Net weight	1.27kg	/
	Gross weight	2.22kg	/
	Product dimensions	261*179*39mm (L*W*H)	/
	Single Unit Package Dime	411*226*73mm (L*W*H)	/
Other functions	Carton Dimension	420*390*475 (L*W*H) (Ctn Qty:10 pcs)	/
	Camera	2 megapixels	5 megapixels/8 megapixels
	NFC	NO	Customizable
	RFID	NO	Customizable
OEM	POE	NO	Customizable
	Appearance, Interface, CPU, Logo, etc.		

The specifications provided in this document represent the standard configuration. For customized solutions or more detailed technical information, please do not hesitate to contact us.